

SD3500v 5Gbps USB 3.0 Dual 2K Docking Station - HDMI/DVI-I/VGA - Windows

Make a Windows Laptop or Convertible Ultra-Productive

K33972EU



Product information

Depth	125mm
Width	69mm
Height	194mm
Gross weight	0.77kg

Retail Packaging Information

Depth	80mm
Width	165mm
Height	190mm
Gross weight	0.96kg
UPC#	5028252351898
Unit quantity	1

Master Case Information

Depth	345mm
Width	270mm
Height	190mm
Gross weight	4.40kg
UPC#	5028252351904
Unit quantity	4

Shipping Information

Country of origin	CN
Minimum Order Quantity	1

General information

Colour	Black
--------	-------

Product Description

Ultra-thin laptops and 2-in-1 convertibles like the Microsoft Surface Pro offer great mobile productivity and sleek good looks. But that also means they usually come up short on connectivity ports. As a result, you're constantly plugging and unplugging peripherals. That's where the SD3500v USB 3.0 Universal Docking Station comes in. It turns one USB port into six so you have access to all your peripherals, including keyboard, mouse, printer and external hard drive. And with dual HD video output, you can add two external monitors to boost productivity. The dock's two USB 3.0 ports support super-speed data transfer of up to 5 Gbps.

Features

- Best for: USB 3.0 Laptops, Ultrabooks & Windows Tablets and Monitors that support up to 2K
- Connection technology: USB 3.0 (DisplayLink)
- Compatibility: Windows 7 or above, macOS 10.14
- No of monitors supported: 2
- Video ports: 1 x HDMI v1.2 and 1 x DVI-I (DVI-to-VGA and DVI-to-HDMI supported with included adapters)
- Resolution: Single Monitor: 1920 x 1200 @ 60Hz and Dual Monitors: 2048 x 1152 @ 60Hz
- DisplayLink driver installation required Download software from Kensington.com or via Windows update.
- Warranty: 2 Years

Specifications

- **Connection technology** USB 3.0 (DisplayLink)
- **Driverless** No
- **Number of Screen Outputs** 2
- **Video ports** DVI-I, HDMI, VGA
- **Maximum resolution** 2K
- **Operating system(s)** macOS, Windows
- **Number of USB ports** 6
- **USB fast charging** No